
Temperature Sensor

FXDD005

Part Number

Technical Data



weFlux² InoxSens

140

21

901

Suitable Mounting Technology No.

* Tested by wenglor


Suitable Connection Technology No.

Connection Diagram No.



- FDA compliant
- Response time T90: < 2 seconds
- Robust stainless steel housing with IP69K
- Temperature measuring range: -50 ... +200° C


weFlux² Temperature Sensors ensure precise temperature measurement of liquids and gases in closed piping systems. It's easy to incorporate the standardized PT100/PT1000 resistance value into the controller. The compact housing with a diameter of just 27 mm is made of V4A stainless steel and features an easy-to-clean surface. Thanks to their rugged housing and functional design, the Temperature Sensors are FDA compliant.




Complementary Products

Seal G1/4" ZH5G001







.egen	nd		PT	Platinum measuring resistor	ENA	Encoder A	
+	Supply Voltage +		nc	not connected	ENB	Encoder B	
-	Supply Voltage 0 V		U	Test Input	Amin	Digital output MIN	
~	Supply Voltage (AC Voltage)		Ū	Test Input inverted	Амах	Digital output MAX	
Α	Switching Output	(NO)	W	Trigger Input	Аок	Digital output OK	
Ā	Switching Output	(NC)	0	Analog Output	SY In	Synchronization In	
V	Contamination/Error Output	(NO)	0-	Ground for the Analog Output	SY OUT	Synchronization OUT	
V	Contamination/Error Output	(NC)	BZ	Block Discharge	OLT	Brightness output	
E	Input (analog or digital)		Awv	Valve Output	М	Maintenance	
Т	Teach Input		а	Valve Control Output +			
Z	Time Delay (activation)		b	Valve Control Output 0 V			
S	Shielding		SY	Synchronization		Wire Colors according to DIN IEC 757	
RxD	Interface Receive Path		E+	Receiver-Line	DIN IE		
TxD	Interface Send Path		S+	Emitter-Line	BK	Black	
RDY	Ready		±	Grounding	BN	Brown	
GND	Ground		SnR	Switching Distance Reduction	RD	Red	
CL	Clock		Rx+/-	Ethernet Receive Path	OG	Orange	
E/A	Output/Input programmable		Tx+/-	Ethernet Send Path	YE	Yellow	
•	IO-Link		Bus	Interfaces-Bus A(+)/B(-)	GN	Green	
PoE	Power over Ethernet		La	Emitted Light disengageable	BU	Blue	
IN	Safety Input		Mag	Magnet activation	VT	Violet	
OSSD	Safety Output		RES	Input confirmation	GY	Grey	
Signal	Signal Output		EDM	Contactor Monitoring	WH	White	
BI_D+/-	Ethernet Gigabit bidirect. data line (A-D)		ENARS422	Encoder A/Ā (TTL)	PK	Pink	
- Nnesse	Encoder 0-pulse 0-0 (TTL)			Encoder B/B (TTL)	GNYE	Green/Yellow	











